

ITC Power



**DEUTZ
ENGINE**


DD65KSE

Diesel Generator

50Hz Standby 64.6KVA 3 phase



Prime Power (kVA)	59
Prime Power (kW)	47
Standby Power (KVA)	65
Standby Power (KW)	52
Power Factor	0.8
Frequency (Hz)	50
Rate Voltage (V)	400/230
Rate Current (A)	85
Controller	MRS10
Control Voltage (DC/V)	24
Battery Capacity (Ah)	60 × 2
Coolant Capacity (L)	15.9
Fuel Tank Capacity(Base frame) (L)	180
Fuel Consumption (L/Hour)	13.7
Running Time (Hour)	13.1
Sound @7 meter (dBA)	68
Open Type Product size (mm)	1955 × 950 × 1360
Open Type Weight net (kg)	995
Canopy type product size (mm)	2500 × 950 × 1520
Canopy Type Weight net (kg)	1290
Engine Model	BF4M2012
Prime power (kW)	54
Structure	4 cylinders, inline
Fuel type	Diesel
Fuel consumption (L/Hour)	13.7
Lubricant consumption (L/Hour)	0.02
Governor	Mechanical
Cooling	Water
Lubricant capacity (L)	8.5
Air intake flow (m ³ /min)	3.7
Exhaust gas flow (m ³ /min)	8.8
Exhaust gas temperature (°C)	610
Exhaust gas back pressure (Kpa)	3
Compression ratio	19
Aspiration	Turbocharging
Bore (mm)	101
Stroke (mm)	126
Displacement (L)	4.04
SAE	3/11.5
Dimension (mm)	1302.5 × 661.5 × 971
Net weight (Kg)	457
Alternator Model (STAMFORD)	UCI224E
Prime power (kVA)	60
Alternator Model (ITC Power)	224E
Prime power (kVA)	60
Structure	1 Bearing
Excitation mode	Self-excitation
Insulation class	H
Protection class	IP23
TIF	<50
THF	<2%
Air flow (m ³ /s)	0.216
AVR Model	SX460



Support engine and alternator monitoring, measurement and protection. This is long-running and back-up unit to integrate the best way to control. support Modbus standard, modem, RS232, RS485, USB and internet.

Measurement, displayment	MRS10
Genset prime power Kw	●
Power factor	●
Engine speed	●
Phase to neutral voltage	●
Phase to phase voltage	●
Genset frequency	●
Genset current	●
Mains Phase to neutral voltage	×
Mains Phase to phase voltage	×
Mains frequency	×
Engine oil pressure	●
Engine water temperature	●
Fuel level	●
Battery voltage	●
Genset power KVA	●
Genset running time	●
Genset output KWh	×
History file	×
Alarm, shutdown function	
Low oil pressure warning, shutdown	●
High water temperature warning, shutdown	●
Engine over and under speed shutdown	●
Low fuel level warning, shutdown	●
Battery low and high voltage warning	●
Battery charging failure	●
Genset low and high voltage warning, shut down	●
Alternator 3 phase voltage unbalance shut down	●
Alternator low and high frequency warning, shut down	●
Genset over load shutdown	●
Alternator 3 phase current unbalance shutdown	●
Mains low and high voltage warning	×
Mains low and high frequency warning	×
Optional	
Remote start and stop	●
RS232 card	○
USB card	○
RS485 card	○
Multi language display	○
GPRS communication	○
GPS communication	×